

GOLD COAST GENERATORS
 Unit 14, 225A Brisbane Road
 Labrador, QLD 4216
 Tel: (07) 5529 0351 Fax: (07) 5529 0416
 Email: Info@goldcoastgenerators.com.au

DGUH6.5/3S-2 or DGUH6.5E/3S-2



This **3 phase** industrial generator is strong and gutsy, built for farmers and tradesmen. High output, up to 6000 watts, puts this generator towards the top of the list for compact, instant, portable **3 phase** power. Choice of recoil or electric start Honda Engine.

Ideal for running power tools, hand tool and electric motors up to 1.25hp (1 kW). Lighting and small appliances for domestic use and camping applications.

RATING NOTES

kVA @ 0.8 pf (standby)	7kVA	kW	6000/3
Volts	240	Frequency	50 hZ

TECHNICAL INFORMATION

Engine Model	GX390	Engine Type	Honda
Engine Power	13 HP	Continuous Watts	6000/3
Noise Level @ 7 mtrs	76 dbl	Operation Hours (@ 80%)	2.8 hrs
Fuel Capacity	6.5L	Fuel Type	Unleaded Petrol
Start Method	S-2 – Recoil ES-2 - Electric		

DIMENSIONAL & WEIGHT INFORMATION

Length	810mm	Width	520mm
Height	525mm	Dry Weight	S-2 - 80 kg ES-2 – 85 kg

Note: Electric start engines include battery and lead

Spec details valid as of Dec '08 & subject to change without notice